

# Release Notes

**HP Integrity Entry-level Servers for Microsoft Windows Server 2003**



**Manufacturing Part Number: 5990-8260**

**April 2005**

© Copyright 2005  
Hewlett-Packard Development Company, L.P.  
All rights reserved.

---

## Legal Notices

© 2005 Hewlett-Packard Development Company, L.P.

Confidential computer software. Valid license from HP required for possession, use or copying. Consistent with FAR 12.211 and 12.212, Commercial Computer Software, Computer Software Documentation, and Technical Data for Commercial Items are licensed to the U.S. Government under vendor's standard commercial license.

The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

Microsoft and Windows are U.S. registered trademarks of Microsoft Corporation. Intel and Itanium are registered trademarks of Intel Corporation or its subsidiaries in the United States and other countries. Linux is a U.S. registered trademark of Linus Torvalds.

# Release Notes

Using the Intel® Itanium® 2 processor or the HP mx2 dual-processor module and the HP Scalable Processor Chipset zx1, **HP Integrity entry-level servers** running Microsoft® Windows® Server 2003 Enterprise Edition with SP1 for Itanium-based Systems deliver high performance, great flexibility, and simplified management at an exceptional value. The HP Integrity entry-level servers include the following server models:

<b>rx5670</b>	<ul style="list-style-type: none"> <li>• 1-4 Intel® Itanium® 2 processors</li> <li>• 1 TB memory capacity</li> <li>• 10 PCI-X slots</li> </ul>
<b>rx4640</b>	<ul style="list-style-type: none"> <li>• 1-4 Intel Itanium 2 processors or HP mx2 dual processor modules</li> <li>• 1 TB memory capacity</li> <li>• 8 PCI-X slots (6 of those with hot-plug functionality)</li> </ul>
<b>rx2620</b>	<ul style="list-style-type: none"> <li>• 1-2 Itanium 2 processors</li> <li>• 1 TB memory capacity</li> <li>• 4 PCI-X slots</li> <li>• Two 1 GB LAN ports</li> </ul>
<b>rx2600</b>	<ul style="list-style-type: none"> <li>• 1-2 Itanium 2 processors</li> <li>• 1 TB memory capacity</li> <li>• 4 PCI-X slots</li> <li>• 1GB single channel NIC (embedded)</li> <li>• 10/100 NIC (embedded)</li> </ul>
<b>rx1620</b>	<ul style="list-style-type: none"> <li>• 1-2 Itanium 2 processors</li> <li>• 1 TB memory capacity</li> <li>• 2 PCI-X slots</li> <li>• Two 1 GB LAN ports</li> </ul>

---

## NOTE

---

With the launch of the rx1620 and rx2620, the management processor (MP) is renamed **Integrated Lights Out (iLO)** on entry-level HP Integrity servers.

---

## What's New in Smart Setup 3.30

This release supports **Service Pack 1 (SP1)** for Microsoft Windows Server 2003, 64-bit, and provides critical updates to the following components:

***System Management Homepage (SMH)*** version 2.0.0.104

Includes a bug fix that corrects the display of the Complex Event Viewer page.

***U320 SCSI driver*** version 1.10.5.1

Updates the driver for the U320 SCSI Host Bus Adapter.

---

### NOTE

The Smart Setup CD does not contain SP1. HP provides a separate Datacenter Update DVD to existing customers running Microsoft Windows Server 2003, Datacenter Edition, on HP Integrity servers. Microsoft provides SP1 at the Microsoft download web site and on the Windows Server 2003 OS with SP1 retail media.

---

---

## Software Requirements

In addition to the software included from HP, the following software is required.

### Java

- Partition Manager requires JDK (32-bit) 1.4.1 or 1.4.2 available from the Sun Microsystems download site: <http://java.sun.com>
- Integrity Management Agents require JRE 1.4.1 or 1.4.2 available from the Sun Microsystems download site: <http://java.com>

### Web Browser

RMU, the browser-based interface to the Smart Setup CD, requires Internet Explorer version 5.0 or higher. The latest version of Internet Explorer is available from the Microsoft download site: <http://www.microsoft.com/windows/ie/default.msp>

### TCP/IP and SNMP

HP Insight Management Agents require installation and configuration of TCP/IP and SNMP. SNMP installation must be done manually.

## Supported components

The following tables list the supported components of each server:

### rx5670

<b>Operating System</b>	<ul style="list-style-type: none"> <li>Windows Server 2003, Enterprise Edition with SP1 for Itanium-based Systems</li> </ul>
<b>LAN Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI 10/100Base-T LAN adapter V. 7.0.26 (P3492A)</li> <li>HP PCI 1000Base-T Gigabit Ethernet Adapter for Windows V. 7.86 (A7061A)</li> <li>HP PCI 1000Base-SX Gigabit Ethernet Adapter V. 7.86 (A7073A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet SX adapter card V. 7.2.17.8 (A9899A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet TX adapter card V. 7.2.17.8 (A9900A)</li> </ul>
<b>SCSI Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI Single Channel Ultra160 SCSI Adapter for Windows (A7059A)</li> <li>HP PCI Dual Channel Ultra160 SCSI Adapter for Windows (A7060A)</li> <li>HP PCI-X Dual Channel Ultra320 SCSI Host Bus Adapter (A7173A)</li> </ul>
<b>Fibre Channel Adapter</b>	<ul style="list-style-type: none"> <li>HP StorageWorks 2 Gb Fibre Channel HBA (AB232A)</li> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Dual Channel HBA (AB466A)</li> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Single Channel HBA (AB467A)</li> <li>HP StorageWorks 2 Gb Fibre Channel Host Bus Adapter (A7298A)</li> </ul>
<b>RAID Controller</b>	<ul style="list-style-type: none"> <li>HP 2-channel Smart Array 5302, Ultra160 SCSI (A9825A)</li> <li>HP 4-channel Smart Array 5304, Ultra160 SCSI (A9826A)</li> </ul>
<b>VGA Graphics</b>	<ul style="list-style-type: none"> <li>HP Graphics/USB card (A6869A in the I/O chassis attached to the root cell only)</li> </ul>

## rx4640

<b>Operating System</b>	<ul style="list-style-type: none"> <li>Windows Server 2003, Enterprise Edition with SP1 for Itanium-based Systems</li> </ul>
<b>LAN Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI 1000Base-T Gigabit Ethernet Adapter for Windows V. 7.86 (A7061A)</li> <li>HP PCI 1000Base-SX Gigabit Ethernet Adapter V. 7.86 (A7073A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet SX adapter card V. 7.2.17.8 (A9899A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet TX adapter card V. 7.2.17.8 (A9900A) (AB352-60001 for core NIC)</li> </ul>
<b>SCSI Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI Single Channel Ultra160 SCSI Adapter for Windows (A7059A)</li> <li>HP PCI Dual Channel Ultra160 SCSI Adapter for Windows (A7060A)</li> <li>HP PCI-X Dual Channel Ultra320 SCSI Host Bus Adapter (A7173A/Core I/O)</li> </ul>
<b>Fibre Channel Adapter</b>	<ul style="list-style-type: none"> <li>HP StorageWorks 2 Gb Fibre Channel HBA (AB232A)</li> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Dual Channel HBA (AB466A)</li> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Single Channel HBA (AB467A)</li> <li>HP StorageWorks 2 Gb Fibre Channel Host Bus Adapter (A7298A)</li> </ul>
<b>RAID Controller</b>	<ul style="list-style-type: none"> <li>HP PCI-X 2-channel Smart Array 6402, Ultra320 SCSI (A9890A)</li> </ul>

## rx2620

<b>Operating System</b>	<ul style="list-style-type: none"> <li>Windows Server 2003, Enterprise Edition with SP1 for Itanium-based Systems</li> </ul>
<b>LAN Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI 10/100Base-T LAN adapter V. 7.0.26 (P3492A)</li> <li>HP PCI 1000Base-T Gigabit Ethernet Adapter for Windows V. 7.86 (A7061A)</li> <li>HP PCI 1000Base-SX Gigabit Ethernet Adapter V. 7.86 (A7073A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet SX adapter card V. 7.2.17.8 (A9899A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet TX adapter card V. 7.2.17.8 (A9900A)</li> </ul>
<b>SCSI Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI Single Channel Ultra160 SCSI Adapter for Windows (A7059A)</li> <li>HP PCI Dual Channel Ultra160 SCSI Adapter for Windows (A7060A)</li> <li>HP PCI-X Dual Channel Ultra320 SCSI Host Bus Adapter (A7173A/Embedded)</li> </ul>
<b>Fibre Channel Adapter</b>	<ul style="list-style-type: none"> <li>HP StorageWorks 2 Gb Fibre Channel HBA (AB232A)</li> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Dual Channel HBA (AB466A)</li> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Single Channel HBA (AB467A)</li> <li>HP StorageWorks 2 Gb Fibre Channel Host Bus Adapter (A7298A)</li> </ul>
<b>RAID Controller</b>	<ul style="list-style-type: none"> <li>HP 2-channel Smart Array 5302, Ultra160 SCSI (A9825A)</li> <li>HP 4-channel Smart Array 5304, Ultra160 SCSI (A9826A)</li> <li>HP PCI-X 2-channel Smart Array 6402, Ultra320 SCSI (A9890A)</li> </ul>



## rx2600

<b>Operating System</b>	<ul style="list-style-type: none"> <li>Windows Server 2003, Enterprise Edition with SP1 for Itanium-based Systems</li> </ul>
<b>LAN Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI 10/100Base-T LAN adapter V. 7.0.26 (P3492A)</li> <li>HP PCI 1000Base-T Gigabit Ethernet Adapter for Windows V. 7.86 (A7061A)</li> <li>HP 1000Base-SX Gigabit Ethernet Adapter V. 7.86 (A7073A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet SX adapter card V. 7.2.17.8 (A9899A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet TX adapter card V. 7.2.17.8 (A9900A)</li> </ul>
<b>SCSI Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI Single Channel Ultra160 SCSI Adapter for Windows (A7059A)</li> <li>HP PCI Dual Channel Ultra160 SCSI Adapter for Windows (A7060A)</li> <li>HP PCI-X Dual Channel Ultra320 SCSI Host Bus Adapter (A7173A/Embedded)</li> </ul>
<b>Fibre Channel Adapter</b>	<ul style="list-style-type: none"> <li>HP StorageWorks 2 Gb Fibre Channel HBA (AB232A)</li> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Dual Channel HBA (AB466A)</li> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Single Channel HBA (AB467A)</li> <li>HP StorageWorks 2 Gb Fibre Channel Host Bus Adapter (A7298A)</li> </ul>
<b>RAID Controller</b>	<ul style="list-style-type: none"> <li>HP 2-channel Smart Array 5302, Ultra160 SCSI (A9825A)</li> <li>HP 4-channel Smart Array 5304, Ultra160 SCSI (A9826A)</li> <li>HP PCI-X 2-channel Smart Array 6402, Ultra320 SCSI (A9890A)</li> </ul>

## rx1620

<b>Operating System</b>	<ul style="list-style-type: none"> <li>Windows Server 2003, Enterprise Edition with SP1 for Itanium-based Systems</li> </ul>
<b>LAN Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI 1000Base-T Gigabit Ethernet Adapter for Windows V. 7.86 (A7061A)</li> <li>HP PCI 1000Base-SX Gigabit Ethernet Adapter V. 7.86 (A7073A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet SX adapter card V. 7.2.17.8 (A9899A)</li> <li>HP PCI-X Dual Port Gigabit Ethernet TX adapter card V. 7.2.17.8 (A9900A)</li> </ul>
<b>SCSI Adapter</b>	<ul style="list-style-type: none"> <li>HP PCI-X Dual Channel Ultra320 SCSI Host Bus Adapter (A7173A/Embedded)</li> </ul>
<b>Fibre Channel Adapter</b>	<ul style="list-style-type: none"> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Dual Channel HBA (AB466A)</li> <li>HP StorageWorks 2 Gb, 64-Bit/133 MHz PCI-X-to-Fibre Single Channel HBA (AB467A)</li> </ul>
<b>RAID Controller</b>	<ul style="list-style-type: none"> <li>HP PCI-X 2-channel Smart Array 6402, Ultra320 SCSI (A9890A)</li> </ul>

### NOTE

#### **For HP Integrity rx1620, rx2600, rx2620, and rx5670 servers:**

Windows Server 2003 supports 256 MB, 512 MB, 1 GB, and 2 GB DIMMs only. *It does not support 4 GB DIMMs.* Therefore, when migrating from another OS to Windows Server 2003 on servers where 4 GB DIMMs are currently installed, you must first replace the 4 GB DIMMs with supported ones.

## Troubleshooting common issues

Please read this section completely before installing or running Windows Server 2003 on HP Integrity servers. This section includes workarounds that may save you valuable time and effort.

### Array Configuration Utility (ACU)

all Integrity  
servers

#### ACU cannot be used when Windows Driver Verifier (verifier.exe) is running in the background

- Issue** ACU reports incorrect results when the Windows Driver Verifier is enabled and running in the background.
- Workaround** There is no workaround at this time. If you want to run the ACU, you must first end the “verifier.exe” process using the Windows Task Manager, then launch ACU. Do not run both simultaneously.

### Fibre Channel

all Integrity  
servers

#### LPutil64 DELETE button does not delete the selected EFI driver or firmware

- Issue** The LPutil64 **Delete** button does not work with the A7298A, AB232A, AB466A, or the AB467A adapters.
- Workaround** Disable the desired EFI driver using LPutil64's **Enable/Disable** button instead. Another solution is to simply flash to a newer version of the EFI driver, which will overwrite the existing version.

### Installation

all Integrity  
servers

#### Blank screen during system startup

- Issue** During system startup the screen may remain blank for 3 to 8 minutes (actual time depends on the quantity of the installed system memory).
- Workaround** This is normal. The system activity can be monitored within a few seconds of system power-on via a remote terminal.

all Integrity  
servers

#### Do not use the 16GB option when installing the OS from the re-install media

- Issue** If you use the 16 GB option during installation of the OS from re-install media, you cannot create a kernel memory dump (in the event of a system failure) unless the page file size is manually configured afterward. In addition, even with manual configuration the page file size will still be less than the recommended 20GB.
- Workaround** The system partition must be created on a 33 GB or larger disk drive. When using re-install media, choose either the 33 GB or max drive size option when configuring the system volume.

**all Integrity  
servers**

**Use Esc8 instead of F8 key on a headless server**

- Issue** The Telnet and Hyperterminal applications on Windows NT4 and Windows 2000 do not correctly map the ASCII string for the function keys. For example, during Power On Self Test (POST) the Smart Array firmware will display a banner and configuration menu with instructions to press the **Esc** key to continue or the **F8** key to enter the configuration utility. When running the system in a headless configuration, pressing **F8** does not display the configuration menu.
- Workaround** To transmit the correct ASCII string using these applications from a remote terminal, press the **Esc** key immediately followed (within 1 second) by the numeric value of the desired function key. For example, to send the ASCII string for **F8**, press the **Esc** key immediately followed by pressing the **8** key (if the terminal emulator is set to UTF-8, then you can press the **F8** key instead). An easier solution to both problems is to simply use PuTTY instead of Telnet or Hyperterminal. PuTTY is a terminal emulator available on your Smart Setup media.

**Management Agents**

**all Integrity  
servers**

**New Insight Agents smart component does not detect older versions**

- Issue** Insight Management Agents for Integrity servers version 3.0 does not indicate that it is overwriting an older version (2.4, 2.3, and so on) of the Agents. The newer smart component does not detect the older component.
- Workaround** No work around is necessary because there is no impact on functionality. No user action is needed.

**all Integrity  
servers**

**The smart component for management agents displays an “installation failed” message during an upgrade if the old version is identical to the new version.**

- Issue** The Insight Management Agents smart component on Smart Setup 3.30 and Smart Setup 3.20 are identical. If you try to install the 3.30 version on a system where the 3.20 version is already installed, the smart component displays a generic “installation failed” message. This message should indicate that installation is not needed because the new version is identical to the old version.
- Workaround** This has no impact on functionality. No user action is needed.

**SCSI**

**all Integrity  
servers**

**Event ID 117 in Windows event log when using an embedded U320 SCSI controller as external disk drive controller**

- Issue** When using Microsoft Windows Server 2003 on an HP Integrity server with an embedded U320 SCSI controller as the external disk drive controller, intermittent Event ID 117 entries may be generated in the Windows Event Log after rebooting.
- Workaround** Ignore these events. They represent a timeout condition that does not cause any system problems or data loss.

## Service Pack 1 (SP1)

all Integrity  
servers

### Windows Firewall blocks network access after SP1 installation

- Issue** As a part of the security enhancements introduced in SP1, Windows Firewall is turned on by default after SP1 completes installation. The firewall blocks all TCP and UDP communication by default. As a result, several services such as SNMP and Remote Desktop Protocol are unable to establish connections.
- Workaround** After SP1 installs, use the Security Configuration Wizard or configure the Windows Firewall in compliance with your site's security policy. You may need to specify certain services as exceptions in order to restore connections. For more information, refer to the Microsoft documentation and online help on Windows Firewall.

## Smart Array

all Integrity  
servers

### Smart Array 640x/530x generates errors in system event log (Event ID 9)

- Issue** Under extremely heavy I/O conditions the Smart Array driver (cpqcissm) may generate Event ID 9 errors in the system event log.
- Workaround** Ignore these events, as they do not cause any problems or loss of data. There is no fix at this time.

all Integrity  
servers

### Smart Array 6402 as internal disk drive controller generates errors in system event log (Event ID 9 and Event ID 117)

- Issue** When running the Smart Array 6402 as the internal disk drive controller, intermittent Event ID 9 and Event ID 117 entries may be generated in the Windows Event Log after a reboot.
- Workaround** Ignore these events, as they do not cause any problems or loss of data. There is no fix at this time.

all Integrity  
servers

### Storage Works 43xx enclosures in split bus configuration with single power supply may report errors and fail the logical volumes when attached to certain Smart Array controllers

- Issue** StorageWorks 43xx enclosures in a dual bus configuration with an Ultra3 Dual Bus I/O Module and a single power supply may report errors and fail the logical volumes when attached to certain Smart Array controllers. Port A of the StorageWorks 43xx enclosure may intermittently report that all drives installed in the lower bays (Port A, bays 1-7) have been hot plug replaced even when they have not. As a result, the array controller may fail the logical volumes, causing data to become inaccessible, or causing the server to hang or blue screen if the operating system is running from those drives. When the server is rebooted, the drives appear to be working properly; however, some data may be inaccessible. The Power-On Self-Test (POST) does not indicate an error either. The problem occurs regardless of the position of the power supply or fans in the enclosure. This affects any StorageWorks enclosure Model 4314R, Model 4314T, or Model 4354R in a dual bus configuration with an Ultra3 Dual Bus I/O Module and a single power supply, attached to either Smart Array 6402 controller.

	<p><b>Workaround</b> Operate StorageWorks enclosures with a minimum of two power supplies.</p>
all Integrity servers	<p><b>Unable to access the “Smart Array Option ROM Configuration for Arrays Utility”</b></p> <p><b>Issue</b> Inability to access the “Smart-Array Option ROM Configuration for Arrays Utility” menu of the Smart Array controller in the root cell I/O chassis (core I/O chassis) when the <b>F8</b> key is pressed on the USB keyboard during system boot. NOTE: This problem only occurs if you are configuring the Smart Array using the USB keyboard connected to the HP Graphics and USB card. The serial console from the iLO should work fine.</p> <p><b>Workaround</b> Do the following:</p> <ol style="list-style-type: none"> <li>1. Boot the system to the EFI shell.</li> <li>2. At the EFI prompt, enter the following: <code>search &lt;core cell&gt;</code>. For example, enter <code>search 0</code> if the core cell is 0.</li> <li>3. When you see the Smart-Array Option ROM Configuration for Arrays Utility menu, press the <b>F8</b> key on the USB keyboard.</li> <li>4. Now you should see the Smart-Array Option ROM Configuration for Arrays Utility menu.</li> </ol>
rx5670, rx4640, rx2620, rx2600, rx1620	<p><b>Smart Array 640x/530x controllers do not automatically rebuild the internal HDD array when a failed drive is replaced</b></p> <p><b>Issue</b> Smart Array 530x/640x controllers do not automatically rebuild the internal disk array when failed drives are replaced. The server backplane does not provide the manageability features needed for Smart Array adapters to recognize when drives are hot inserted into the system.</p> <p><b>Workaround</b> By installing the Smart Array Rescan Service, the rebuild is initiated automatically after drive replacement:</p> <ol style="list-style-type: none"> <li>1. Download and flash the latest Smart Array firmware available from <a href="http://www.hp.com/support/itaniumservers">www.hp.com/support/itaniumservers</a>. NOTE: Minimum firmware revision for the SA640x controller is 2.28. Minimum firmware revision for the SA530x controller is 3.56.</li> <li>2. Download and install the latest Array Configuration Utility (ACU-XE) from <a href="http://www.hp.com/support/itaniumservers">www.hp.com/support/itaniumservers</a>. The minimum required revision for the ACU-XE is 7.15.18.0.</li> <li>3. Download and install the Smart Array Rescan Service from <a href="http://www.hp.com/support/itaniumservers">www.hp.com/support/itaniumservers</a>. The minimum required revision for the Rescan Service is 0.1.</li> <li>4. If an internal HDD array fails, replace the failed physical drive. The Rescan Service will initiate the rebuild automatically (it may take up to 5 minutes before the rebuild starts). To start the rebuild immediately, open the Array Configuration Utility (ACU-XE) and select <b>Refresh</b> in the Controller State field, and the failed array will begin to rebuild.</li> </ol>

## System Management Homepage (SMH)

all Integrity  
servers

### System Management Homepage fails to open

**Issue** If Internet Explorer is configured to browse through a proxy server and you forget to select the “Bypass proxy server for local addresses” checkbox, attempting to connect to the local SMH (<https://localhost:2381>) fails with a “page cannot be displayed” error.

**Workaround** Configure Internet Explorer to bypass the proxy server for local addresses:

1. In IE, click **Tools > Internet Options**.
  2. Click the **Connections** tab.
  3. Click the **LAN Settings** button.
  4. Under “Proxy Server”, select the **Bypass proxy server for local addresses** checkbox.
- Another solution is to simply change the SMH shortcut (the icon on the desktop) so that it points to <https://127.0.0.1:2381> instead of <https://localhost:2381>.

all Integrity  
servers

### System Management Homepage may log errors to the Windows application event log

**Issue** If SMH is frequently installed and then uninstalled, or if the SMH service is frequently stopped and then started again, the following error can be logged to the Windows application event log:  
Faulting application smhstart.exe, version 2.0.0.103, faulting module unknown, version 0.0.0.0, fault address 0x00000000.

**Workaround** This message does not affect SMH operation. The application should still work normally. In the unlikely event of program termination, uninstall SMH, remove the C:\hp\hpsmh directory, and reinstall SMH.

## Version Control

all Integrity  
servers

### Version Control Repository Manager (VCRM) does not start after System Management Homepage (SMH) reinstallation

**Issue** VCRM fails to start if SMH is uninstalled, the system rebooted, and then SMH is reinstalled. This problem occurs only when the system is rebooted between the SMH install and reinstall.

**Workaround** Reinstall VCRM after reinstalling SMH.

all Integrity  
servers

### Version Control Repository Manager (VCRM) does not upload the Japanese Support Pack from Japanese OS

**Issue** VCRM uploads the English Support Pack instead of the Japanese Support Pack when used on a Japanese OS.

**Workaround** Before uploading the Support Pack on a Japanese OS, change the browser's language setting to "en" or "en-us", upload the Japanese Support Pack, and then switch the browser's language setting back to Japanese.



## Installing Windows Server 2003

When you purchase an HP Integrity server, you can have Windows Server 2003 installed at the factory or install it yourself. The HP Smart Setup media provides tools for installing the OS and updating your server firmware. The following provides instructions on installing Windows Server 2003 on the HP Integrity server using the HP Smart Setup media and your license for Windows Server 2003.

The OS can be installed from either a local or remote console. Installing the OS involves preparing the server for the install, booting from the HP Smart Setup media, running EBSU, launching Windows Setup, loading OS files to the boot disk, booting the server from the boot disk, and specifying system settings.

### Prepare the server for install

- Step 1.** Ensure that all server hardware is Windows compatible.
- Step 2.** If you are migrating from another OS, make sure your data is backed up and recoverable.
- Step 3.** Be sure to disconnect all unnecessary disk controllers, including SAN controllers.
- Step 4.** Set up a local console and install a VGA card if you are installing from a local console. This step is optional.
- Step 5.** Connect a PC running PuTTY Version 0.57 or greater or HyperTerminal to either the server iLO serial port (null modem cable) or the iLO LAN port (hub required).

### Run EBSU

EBSU provides an easy-to-use interface to flash the firmware, partition the hard disk, install diagnostic tools, configure storage controllers, and run other EFI utilities.

- Step 1.** Load the HP Smart Setup media into the server DVD drive.
- Step 2.** From the EFI Boot Menu, select **Internal Bootable DVD** and press **Enter**.
- Step 3.** EBSU starts and displays the Welcome screen. Select **OK** and press **Enter** to continue.
- Step 4.** From the main menu, select **Express Setup** and press **Enter**.
- Step 5.** EBSU displays the Express Setup introduction. Press **Enter** to continue.
- Step 6.** EBSU displays the firmware update screen, listing each device, its installed firmware version, and the firmware version on the Smart Setup media. Select the device(s) whose firmware you want to update. To continue, select **Next** and press **Enter**.

---

#### NOTE

You may not be able to use EBSU to flash the firmware of some devices. You cannot flash the firmware if the installed version is the same or higher than the version on the Smart Setup media. Also, you cannot use EBSU to flash the iLO (previously called the Management Processor, or iLO) firmware. You must download the latest iLO firmware from the HP Integrity support site: <http://www.hp.com/support/itaniumservers/> and flash it separately.

---



- Step 7.** Specify the disk partitions you want to create (**ESP Only** or **ESP + HPSP + MSR**). We recommend the default—ESP + HPSP + MSR—as a means to simplify the maintenance of your server. Also, specify the option to install the Drive Explorer utility, which enables you to browse a drive in EFI. Select **Next** and press **Enter**.
- Step 8.** Specify the option to install offline diagnostic tools (from the *HP Itanium Processor Family offline diagnostics and utilities CD*). Also, specify the option to launch the Windows OS installer. Select **Setup** and press **Enter**.
- Step 9.** EBSU displays the partition confirmation window. Select **Continue** and press **Enter**.
- Step 10.** EBSU prompts you to insert the Microsoft Windows Server 2003 CD in the DVD drive. Insert the *Microsoft Windows Server 2003 CD* and press **Enter**.

## Run Windows Setup

Windows Setup prompts you to create a system partition on the boot disk if needed, copies the operating system files on to that partition, and attempts to reboot from the boot disk.

- Step 1.** When you insert the Microsoft Windows Server 2003 CD in the DVD drive, it launches Windows Setup. Press **Enter** to start the installation.
- Step 2.** Windows Setup prompts you to select **Express Install** or **Custom Install** (only Express Install is available when installing from a remote console). Express Install minimizes user interaction, selecting various installation options on your behalf. Select **Express Install** by pressing **Enter**.
- Step 3.** If Windows Setup cannot find a system partition, it prompts you to create one. Press **Enter** to continue. Windows creates a partition and then prompts you to format it.
- Step 4.** Select the partition in which you want to install the OS and press **Enter**. Windows formats the partition if necessary, checks the partition for errors, and begins to copy the OS files.
- Step 5.** Monitor the copy process until it completes.

Upon completion, Windows Setup counts down to a reboot. Allow the system to reboot.

## Specify server settings (local console)

To set up Windows Server 2003 after initial boot from the local console:

- Step 1.** When the system boots, Windows displays a screen indicating that an EMS channel (iLO remote port) is present. It may take 2 to 15 minutes for the mouse and keyboard to start operating in this mode.
- Step 2.** When prompted to enter server settings, click **OK**.
- Step 3.** From the *Windows Setup Wizard*, enter the following setup information:
  - 1. In the *License Agreement* window, click **Accept** and then **Next**.
  - 2. In the *Regional and Language Options* window, click **Next**.
  - 3. In the *Your Product Key* window, enter the product key.  
The product key is located on the label attached to the server.

4. In the *Licensing Modes* window, select the license you purchased.
5. In the *Administrator Password* window, enter the server name and a password.
6. In the *Date and Time* window, select the appropriate timezone, and click **Next**.

The server reboots to the EFI Boot Manager.

**Step 4.** From the EFI Boot Menu, select Windows Server 2003. The server boots to Windows.

**Step 5.** Log in to the system with the administrator password you specified earlier.

### Specify system settings (remote console)

To set up Windows Server 2003 after initial boot from a remote console:

**Step 1.** At the SAC> prompt, switch to channel one by pressing **Esc+Tab**.

The system displays the following screen:

```
*****
Name:                               Unattended Setup Channel
Description:                         Provide parameters to automate Setup
Type:                               VT-UTF8
Channel GUID:                       0cfc0ee2-3a27-11d7-8484-806e6f6e6963
Application Type GUID: 00000000-0000-0000-0000-000000000000
Press <esc><tab> for next channel.
Press <esc><tab>0 to return to the SAC channel.
Use any other key to view this channel.
*****
```

**Step 2.** Press any key and then press **Page Down**.

**Step 3.** Accept the license agreement by pressing **F8**.  
On the Windows default terminal emulator, **F8** is **<Esc>8**. Press **8** within two seconds after pressing **Esc**. Otherwise, the system will register only **Esc** and reboot.

**Step 4.** Enter the product key.  
The product key is located on the label attached to the server.

**Step 5.** Enter the administrator password and re-enter to confirm.  
The mini-setup process continues automatically and after completion, reboots the system. Wait for the SAC> prompt to reappear.

**Step 6.** Open a terminal server client and connect to your server's IP address.  
Change the computer name and IP address, if needed.

**Step 7.** On the desktop, open the Online Reference page, scroll to the bottom, and click on the link to **c:\hputils\usercompanyname.com**.

**Step 8.** When prompted, enter company and user name, and click **OK** to complete setup.

---

## Re-installing Windows Server 2003

When you purchase an HP Integrity server, you can select the option to have Windows Server 2003 installed at the factory. Servers with the factory-installed Windows operating system are shipped with the HP Re-installation media, which allows you to restore your server to the factory configuration if needed. The following sections provide instructions on installing Windows Server 2003 on the HP Integrity server using the HP Re-installation media.

### From a local console

Re-installing Microsoft Windows Server 2003 from a local console involves copying the operating system image from the Reinstallation media to the disk and setting up the system. The following sections provide brief instructions, aimed at expert system administrators, on getting the server up and running quickly. For detailed instructions, refer to the *Smart Setup Guide*.

#### Load the operating system

To re-install Windows Server 2003 on the server from a local console:

- Step 1.** Disconnect all mass storage devices from all controllers except the boot controller. Make a note of where the other devices were connected so you can reconnect them after installation completes.

---

#### WARNING

**The system installs to the boot controller detected as adapter zero drive zero. If you do not disconnect all other drives, the system may install to an unintended drive.**

---

- Step 2.** Configure the boot controller and drive.  
If you are using a RAID controller, prepare the controller and select the RAID type according to instructions in the RAID controller documentation.
- Step 3.** Because Windows Server 2003 with SP1 cannot create a boot entry if one already exists you must delete the existing boot entry. To delete the boot entry:
1. Select **EFI Boot Manager Menu > Boot Option Maintenance Menu > Delete Boot Option(s)**
  2. Select a Windows Server 2003 boot entry to delete and press **Enter**.
- Step 4.** Insert the *HP Re-Installation media* in the DVD drive.
- Step 5.** From the EFI boot manager, select **Internal Bootable DVD**, if present.  
If this entry is absent:
1. Select **EFI Shell**.
  2. In the EFI Shell, select the DVD file system.  
For example, if the DVD file system is fs1, type **fs1**:
  3. Start the boot loader by typing **setupldr**
- Step 6.** Click **Re-Install**.

**Step 7.** Select the partition size and click **OK** to continue.

---

**NOTE**

The installation process copies files to the hard disk. It may display 99% complete for a long time. Do not power off the server.

---

**Step 8.** When the installation process displays a dialog box, click **OK** to continue.

**Step 9.** Click **Exit**.

The server reboots to the Windows Server 2003 operating system. Set up the system according the instructions in the following section.

**Specify system settings**

To set up Windows Server 2003 after initial boot from the local console:

**Step 1.** Power on the server.

Windows displays a pop-up screen indicating that an EMS channel (headless server iLO port) is present. It may take 2 to 15 minutes for the mouse and keyboard to start operating in this mode.

**Step 2.** When prompted to enter setup information at the local console, click **OK**.

**Step 3.** Enter the following setup information using the *Windows Setup Wizard*.

1. In the *License Agreement* window, click **Accept** and then **Next**.

2. In the *Regional and Language Options* window, click **Next**.

3. In the *Your Product Key* window, enter the product key.

The product key is located on the label attached to the server.

4. In the *Licensing Modes* window, select the license you purchased.

5. In the *Administrator Password* window, enter the server name and a password.

6. In the *Date and Time* window, select the appropriate timezone, and click **Next**.

The server reboots to the EFI Boot Manager and then boots up Windows Server 2003. You can now log in to the server using the administrator password you selected.

## From a remote console

Re-installing Microsoft Windows Server 2003 from a remote console involves copying the operating system image from the Re-Installation media to the disk and setting up the system. The following sections provide brief instructions, aimed at expert administrators, on getting the server up and running quickly. For detailed instructions, refer to the *Smart Setup Guide*.

### Load the operating system

To install the Windows Server 2003 operating system on the server from a remote console:

**Step 1.** Connect to the target system partition with the terminal emulator.

---

**NOTE**

On Windows XP, the Terminal Services client is available under **Accessories > Communications**. On Windows 2000, you must install the Terminal Services client before you can use it.

---

**Step 2.** Because Windows Server 2003 with SP1 cannot create a boot entry if one already exists you must delete the existing boot entry. To delete the boot entry:

1. Select **EFI Boot Manager Menu > Boot Option Maintenance Menu > Delete Boot Option(s)**
2. Select a Windows Server 2003 boot entry to delete and press **Enter**.

**Step 3.** From the EFI boot manager, select **Internal Bootable DVD**, if present.

If this entry is absent:

1. Select **EFI Shell**.
2. In the EFI Shell, select the DVD file system.  
For example, if the DVD file system is fs1, type **fs1**:
3. Start the boot loader by typing **setupldr**

**Step 4.** At the **SAC>** prompt, type **cmd**.

**Step 5.** Switch to the new command prompt channel by pressing **Esc+Tab**.

**Step 6.** Invoke the installation menu by typing **txtrestore**.

**Step 7.** Select the partition size and click **OK** to continue.

---

**NOTE**

The installation process copies files to the hard disk. It may display 99% complete for a long time. Do not power off the server.

---

**Step 8.** When the installation process completes, the main console or VGA display shows a screen indicating that the EMS was detected. When prompted to use the local console, do *NOT* click OK.

**Step 9.** Return to the remote console and perform system setup as indicated in the following section.

**Specify system settings**

To set up Windows Server 2003 after initial boot from a remote console:

- Step 1.** At the SAC> prompt, switch to channel one by pressing **Esc+Tab**.

The system displays the following screen:

```
*****
Name:                               Unattended Setup Channel
Description:                         Provide parameters to automate Setup
Type:                               VT-UTF8
Channel GUID:                       0cfc0ee2-3a27-11d7-8484-806e6f6e6963
Application Type GUID: 00000000-0000-0000-0000-000000000000

Press <esc><tab> for next channel.

Press <esc><tab>0 to return to the SAC channel.

Use any other key to view this channel.

*****
```

- Step 2.** Press any key and then press **Page Down**.

- Step 3.** Accept the license agreement by pressing **F8**.  
On the Windows default terminal emulator, **F8** is **<Esc>8**. Press **8** within two seconds after pressing **Esc**. Otherwise, the system will register only **Esc** and reboot.

- Step 4.** Enter the product key.  
The product key is located on the label attached to the server.

- Step 5.** Enter the administrator password and re-enter to confirm.

The mini-setup process continues automatically and after completion, reboots the system. Wait for the SAC> prompt to reappear.

- Step 6.** Enter **i** to get the IP address of your server.

- Step 7.** Open a terminal server client and connect to your server's IP address.  
Change the computer name and IP address, if needed.

- Step 8.** On the desktop, open the Online Reference page, scroll to the bottom, and click on the link to **c:\hputils\usercompanyname.com**. This link is available when using HP Reinstallation media only.

- Step 9.** When prompted, enter company and user name, and click **OK** to complete setup.

---

## Technical documentation

Technical documentation for HP Integrity servers running Windows Server 2003 includes the following manuals in English and Japanese. These manuals are available on the HP Smart Setup media and from the HP Integrity support Web site: <http://www.hp.com/support/itaniumservers/>.

### *Smart Setup Guide*

provides instructions for installing, re-installing, or migrating to Windows Server 2003 on HP Integrity servers.

### *nPartition Guide*

provides instructions for creating, configuring, and managing nPartitions on cell-based HP Integrity servers running Windows Server 2003.

### *Kernel Debug Guide*

provides instructions for setting up and running the Windows operating system kernel debugging environment, and provides tips and tricks for troubleshooting the OS.

### *Support Pack and Deployment Utilities User Guide*

provides instructions for using the deployment utility and setup tools to perform routine software maintenance tasks in Windows Server 2003 64-bit server environments.

### *Management Events Reference*

contains a list of the Microsoft Windows Server 2003 and Microsoft Windows Server 2000 Event Log messages associated with SNMP traps, which are generated by the HP Management Agents for Servers for Windows.

### *Management Agents Guide*

provides instructions for installing, configuring, and using HP Insight Management Agents on HP Integrity servers running Windows Server 2003.

## Technical support

To keep your server up to date with the latest firmware, drivers, and utilities, visit the HP technical support web site periodically.

### Get Windows-specific firmware, drivers, and utilities

To obtain the entry-level server firmware, drivers, and utilities applicable to Windows Server 2003:

- Step 1.** Go to <http://www.hp.com/>
- Step 2.** Click **Driver Downloads**.
- Step 3.** On the Support & Driver Downloads page, select **Download drivers and software** and type the model name for your server (rx1620, rx2600, rx2620, rx4640, or rx5670) in the product search field, then click the search tab at the right of the search field.
- Step 4.** On the **specify operating system** page, select **Microsoft Windows Server 2003 64-bit**.
- Step 5.** On the **download drivers and software** web page, download firmware and drivers as required.

### Register for HP support notifications

HP recommends that you register for alerts and notifications to stay informed of updates to the drivers, patches, and other components specific to your server.

Go to <http://www.hp.com/united-states/subscribe/gateway/>